



## Combi-18-Flexi

2 x Flexi-12

2 x Ventus-18

Amplifier recommendation:

Powersoft T604, 4 x 1.250 W/8 Ω, 4 x 1.500 W/4 Ω

## Combi-18sp-Flexi

2 x Flexi-12

1 x Ventus-18

1 x Ventus-18sp

## Flexi-12

<b>Frequency range</b>	54 Hz - 22 kHz (- 10 dB) 70 Hz - 20 kHz (+/- 3 dB)
<b>Coverage range</b>	asymmetric 100° to 50° x 55°
<b>Power handling</b>	500 W AES / 1.000 W program / 2.000 W peak at 8 Ω
<b>Sound pressure</b>	123 dB SPL AES / 126 dB SPL program / 129 dB SPL peak
<b>Components</b>	LF: 1 x 12" bass-midrange driver HF: 1 x 1,4" Compression driver
<b>Connectors</b>	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 1+/1-
<b>Dimensions</b>	651 (h) x 360 (w) x 373,3 mm (d)

## Ventus-18/18sp

<b>Lower cut-off frequency</b>	28 Hz (- 10 dB) 34 Hz (- 3 dB)
<b>Power handling</b>	1.200 W AES / 2.400 W program / 4.800 W peak at 8 Ω
<b>Sound pressure</b>	130 dB SPL AES / 133 dB SPL program / 136 dB SPL peak
<b>Components</b>	1 x 18" Woofer with 4" voice coil
<b>Connectors</b>	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 2+/2-
<b>Dimensions</b>	580 (h) x 580 (w) x 780 mm (d)
<b>Amplifier</b>	4.6 kW, three channels
<b>Power output CH1</b>	2.600 W/ 8 Ω, 2.200 W/ 4 Ω
<b>Power output CH2 &amp; CH3</b>	750 W/ 8 Ω, 1.000 W/ 4 Ω, 750 W/ 2 Ω

